

AJ-MULTITRANSMITTER-W

Multi-transmitter via radio
868MHz Jeweller Wireless
Up to 18 Wired alarm and tamper inputs
Configurable alarm NC/NO or EOLR (NC or NO)
Double tamper anti-opening
Double power output 12V / 1A
Reach in open space 2000 m



Ajax
Radio transmitter with multiple inputs
868MHz Jeweller Wireless
Bidirectional
Internal antenna range open space 2000 m
18 wired alarm and anti-sabotage tamper inputs
Inhibition detection
Tamper-resistant opening
Double power output 12 V / 1 A
Power supply 220 VAC and backup battery 4 or 7 Ah (not included)
Compatibility with third party detectors with wired alarm output and with all Ajax Hubs

Specifications

Brand	Ajax
Frequency	868 MHz Jeweller
Transmission distance	? 2000 m in open space
Anti-inhibition detection	Available
Wired inputs	Up to 18 (alarm and tamper)
Alarm inputs	NO/NC or end-of-line resistance EOLR (NO/NC) / Impulse or bidirectional
End-of-line resistor EOL	From 1 k? to 7.5 k?
Tamper input	NC: Normally Closed
Tamper-resistant opening	Front and back
Power supply output	Two outputs 12 V / 1 A (in total) for wired sensors
Compatibility	Compatible with Ajax Hub, Hub Plus, Hub 2, Hub 2 Plus and ReX
Power	AC 110~250 V, 50/60 Hz
Backup battery	Battery 12 V / 4 or 7 Ah (not included)
Temp. operation	-10 °C ~ 40 °C
Dimensions of the backup battery	150 (H) x 64 (W) x 94 (D) mm
Dimensions	196 (H) x 238 (W) x 100 (D) mm