

TTE GPRS Standard

GSM/GPRS Communication Module

- Installation and Programming Manual
- Operation Instruction
- User Guide

Attention:

This manual contains information on limitations regarding product use and function and information on the limitations as to liability of the manufacturer. The entire manual should be carefully read.

The information in this manual is a subject to change without notice!

Table of contents

1. INTRODUCTION	4
1.1 General Information	4
1.1.1 Functional Features	4
1.1.2 Technical Specifications.....	4
1.1.3 Operation Block Diagrams.....	5
Operation with Eclipse Series Burglary Alarm Panels	5
Operation as Stand-Alone Device.....	6
1.2 Before you start.....	7
1.3 TTE GPRS Standard Models	7
2. HARDWARE INSTALLATION	8
2.1 Serial Connection.....	8
2.1.1 Connection to Eclipse Series Control Panels	8
Eclipse Connection Diagrams	8
2.2 Connection to third-party control panels.....	9
2.3 Programmable Inputs/Outputs	9
Connection diagram for the internal structure of programmable output.....	9
2.4 Basic Installation Steps	10
2.5 TTE GPRS Standard LED Indication	10
2.6 Restore to Factory Settings	11
3. PROGRAMMING WITH ProSTE.....	12
3.1 Reading a Configuration	12
3.2 General Settings Menu.....	13
3.3 Phones Menu.....	15
3.3.1 Phone Number Submenus.....	18
Using “Apply Selected” Button.....	19
3.4 Inputs/Outputs Menu.....	20
3.4.1 Setting the Options for Inputs	20
3.4.2 Setting the Options for Outputs.....	23
3.5 Mobile Operators Settings Menu	24
3.6 Receiver Settings Menu.....	24
3.7 Saving a TDF File	26
3.8 Writing a Configuration	26
4. AJAX WEB User Interface	27
4.1 Creating an Account	27
4.2 Adding a System to Account.....	28
4.3 Online Connection with AJAX SP Pro Server	31
4.4 Operation with System.....	31
5. TTE GPRS Standard – Installation Summary	34
6. USER GUIDE.....	35
6.1 AJAX WEB User Interface	35
6.1.1 Remote Access	35
6.1.2 Main Menus.....	35
6.1.3 System Status	36
Troubles & Areas Control Panel Submenu	36
Zones Control Panel Submenu	38
Control Panel PGMs Submenu	39
IP Cameras Submenu.....	40
6.1.4 View Events	41
6.1.5 Communication Module.....	42
6.2 Mobile TTE Smartphone Application.....	43
6.2.1 Adding a System to Mobile TTE.....	43
6.2.2 Connection to a System.....	44

6.2.3 Operation menus in MobileTTE.....	44
6.2.4 Controlling of PGMs	45
6.2.5 System Main Menu	45
6.3 Voice Management	49
6.3.1 Receiving of Voice messages for Events.....	49
6.3.2 Voice Management Mode – Operation Algorithm.....	50
6.4 SMS Messages for Events.....	51
6.5 Operation via Mobile Phone	51
6.5.1 Remote Resetting of TTE GPRS Standard	52
6.5.2 Checking the Signal Strength.....	52
6.5.3 Changing State of PGM Outputs via CLIP	52
6.5.4 Changing State of PGM Outputs via SMS	53

DOCUMENTATION FEEDBACK

If you have any comments or suggestions on our products' manuals or installation instructions you can email us on:

info@teletek-electronics.bg

Your feedback on product documentation will help us to improve the contents of our manuals and stickers and keep them up-to-date.

Please, include in your feedback email the product name, the revision of the manual or instruction (8-digit number with Revision and date of issue) and the page number.

1. INTRODUCTION

1.1 General Information

TTE GPRS Standard is a universal communication module, designed for operation via serial communication with burglary alarm control panels produced by Teletek Electronics JSC. The module transmits the incoming events through the available GPRS network to AJAX SP Pro server (cloud service) and/or through the available GSM channel to end user or monitoring station – SMS messages, voice messages or push notification messages via MobileTTE. The general application of the module is to send messages for events to monitoring center or end user.

The module can be mounted directly into the panel's box or into a separate small plastic box (SB-U) suitable for wall mounting according the application.

TTE GPRS Standard can be connected also to third-party alarm control panels or to be used as a stand-alone device. The module is suitable for realizing of home automation applications. The module is programmed via ProsTE software or remotely via AJAX Web User Interface.

1.1.1 Functional Features

- Serial communication with Eclipse series burglary alarm control panels
- Allows full management of Eclipse series panels via Mobile TTE smartphone application and AJAX Web User Interface
- Third party alarm panels connected to the inputs
- SIA-DC09 IP protocol messages
- 6 telephone numbers for SMS and voice messaging to end user
- SMS messages for system events
- Voice reporting and Voice guiding (optionally mounted micro SD card)
- AES 128 encryption
- Supports 2G networks
- Main and back-up IP for connection with AJAX SP Pro server
- Micro USB input for direct PC connection
- Jumper for restoring of the default factory settings
- Reversed polarity and overload protection

1.1.2 Technical Specifications

- Main power supply:.....9-30VDC (no tolerance)
- Current consumption:
 - Normal operation mode (standby):50mA
 - Maximal consumption:150mA
- 6 Programmable Inputs/Outputs:up to 100mA each
- Time for filtration of signals incoming at I/O:0.5sec
- Working frequencies:850/ 900/1800/ 1900 MHz
- Antenna connector:SMA 50Ohm, internal mounted
- Operating temperature:..... -20°C ÷ +60°C


Important note:

The purpose of this manual is to give directions for programming the TTE GPRS Standard module, its operation with AJAX SP Pro server, Mobile TTE smartphone application and voice guiding operation. You can refer to the installation manual of the module (applied into the packing box) for details about its elements and PCB hardware.

Find out more materials also at www.teletek-electronics.com.

1.1.3 Operation Block Diagrams

Operation with Eclipse Series Burglary Alarm Panels



1. Security System - Eclipse series Burglary Alarm Panel in serial communication with TTE GPRS Standard module. The TTE GPRS Standard communication module is mounted into the panel's box and is connected via serial interface flat cable to the control panel's PCB – see item [2.1 Serial Connection](#).

2. Program the TTE GPRS Standard module with ProsTE – see item [3. Programming with ProsTE](#).

3. GPRS channel for connection via SIA over IP communication protocol.

4. SIA DC-09 Alarm Receiver and Monitoring Software. Monitoring station of a service security provider operating with SIA-DC09 IP station reporting to monitoring software.

5. AJAX SP Pro Server. This is a computer with installed AJAX SP Pro Server administrative interface. Usually it is situated into a Monitoring station of a service security provider.


6. AJAX WEB. This is a User interface (web site) for management and control of panels and communication modules produced by Teletek Electronics JSC. After registration the User can review the status and to control (ARM, DISARM, Zone BYPASS, etc.) one or more security systems attached to his account.

7. Mobile TTE. This is a smartphone application for management and control of panels and communication modules produced by Teletek Electronics JSC, which are attached to a User account at AJAX WEB. The smartphone application is compatible with iOS and Android platforms.

8. GSM channel. SMS and Voice reporting for events; voice management by end user - Full ARM, DISARM and PGMs control of Eclipse panel (requires mounted micro SD card with recorded voice messages); SMS and CLIP control of module's outputs.

Operation as Stand-Alone Device

This application is suitable for realizing of home automation applications where the User wants to control different electrical appliances via the programmable outputs of the module or to be informed (via Mobile TTE) for non-standard events via the programmable inputs.



1. The TTE GPRS Standard module must be connected to an external power supply unit. Use a suitable unit capable to provide power in range 9-30VDC. Observe the polarity of the connection – “+” terminal of the power unit to “+VDC” terminal of the module, and “-” terminal of the power unit to “-VDC” terminal of the module.

2. Program the TTE GPRS Standard module with ProsTE – see item [3. Programming with ProsTE](#).

3. GPRS channel for connection via SIA over IP communication protocol.

4. AJAX SP Pro Server. This is a computer with installed AJAX SP Pro Server administrative interface. Usually it is situated into a Monitoring station of a security provider.

5. AJAX WEB. This is a User interface (web site) for management and control of panels and communication modules produced by Teletek Electronics JSC. After registration the User can review the status and to control the outputs of the module.

6. Mobile TTE. This is a smartphone application for management and control of panels and communication modules produced by Teletek Electronics JSC and attached to a User account at AJAX WEB. The smartphone application is compatible with iOS and Android platforms. The User can control remotely the outputs of the module and to receive notification messages at inputs activation.

7. GSM channel. SMS and Voice reporting for events (requires mounted micro SD card with recorded voice messages); SMS and CLIP control of module’s outputs.

1.2 Before you start

Before starting you need the following equipment:

- ProsTE Programming Software installed on a local computer or laptop for reading, writing and saving the module's configuration.
- Standard USB-Micro USB data cable.
- Flexible flat cable - 300mm long (not included in the kit, sold separately) for serial connection to Eclipse panel.
- Valid SIM Card supporting 2G networks with disabled PIN protection code.
- Micro SD card with recorded voice messages (option).

And also, is helpful to have prepared:

- A valid account registration in AJAX WEB User interface*.
- An installed Mobile TTE application on your smartphone**.

** For monitoring and management of burglary control panels Eclipse series and module's outputs. Ask your local distributor or security provider how to access the AJAX WEB site and to register an account.*

*** You can download the application from Google Play or App Store according your smartphone model. You will be able to review all attached systems to your AJAX WEB account after adding them into the Mobile TTE application.*

The manufacturer also recommends:

- Review the status of your Eclipse burglary alarm control panel to which the TTE GPRS Standard module is going to be connected. Check the programming and settings for operation with communication equipment.
- Check the subscription plan of the used SIM card and network coverage. The SIM card must support 2G network. To be able to connect to AJAX SP Pro Server and use the Mobile TTE application on your smartphone, your plan must include a mobile internet (at least 100MB data traffic per month) and if you want also to use the SMS control, voice reporting and voice management options - at least 100 minutes per month (it depends on the frequency of use).
- To be able to use the voice reporting and voice management options, your TTE GPRS Standard must be equipped with SD micro card with recorded messages.
- In case the TTE GPRS Standard is going to be used as a stand-alone device, equip it with a suitable external power supply unit providing 9-30VDC.

1.3 TTE GPRS Standard Models

The TTE GPRS Standard communication module is available for purchase in two modifications.

- **TTE GPRS Standard.** The supplied kit includes:

1. PCB of the Module with mounted antenna.
2. Jumper for reset.
3. Short instruction manual for installation.

- **TTE GPRS Standard VG (Model: Voice Guide).** The supplied kit includes:


1. PCB of the Module with mounted antenna.
2. Jumper for reset.
3. Short instruction manual for installation.
4. Micro SD card with recorded voice messages.

2. HARDWARE INSTALLATION

The TTE GPRS Standard is a universal communication module which provides the opportunity for connection to different types of control panels and reporting for events to a monitoring station and/or end User.

2.1 Serial Connection


All panels produced by Teletek Electronics JSC are connected via serial interface connection to TTE GPRS Standard module.



The TTE GPRS Standard is mounted into the panel's installation box and is powered on directly from the control panel via the serial interface. The serial connection between the module and control panel is done with a flexible flat cable 300mm long. Connect the cable to the 6-pin interface terminal on the control panel's PCB.


2.1.1 Connection to Eclipse Series Control Panels

There is an extra free room space for installation of communication and expander modules in Eclipse series installation box.



Eclipse Connection Diagrams


The serial interface cable is connected to *Serial connector* on the Eclipse panel's PCB.



2.2 Connection to third-party control panels

The programmable input/output terminals of the module are used for connection to third-party control panels. The module can be powered on from the *+/-AUX output* (required 9-30VDC) of the control panel to *+VDC and -VDC terminals* as observing the polarity.


In the presented connection example, the IO1 terminal of the module is programmed as an output, and IO2 and IO3 are programmed as inputs via ProsTE software - see item [3.4 Inputs/Outputs Menu](#).



2.3 Programmable Inputs/Outputs

The TTE GPRS Standard has 6 terminals which can be programmed as input or output according the current application. The input/output is programmed with ProsTE software. It is suitable for realizing of home automation.

Connection diagram for the internal structure of programmable output



Attention:

All electrical connections must be done **ONLY** when the mains and back-up power supplies of the module are switched off!

2.4 Basic Installation Steps


1. Turn off the main and backup power supply of the control panel.
2. Place the module as shown on above and fix it on place with suitable screws to the box of the control panel.
3. Connect the module to the panel with the serial flat interface cable as shown on connection diagrams.
4. Switch off the PIN protection code of the SIM card and place it into the SIM interface holder of the TTE GPRS Standard module.
5. For TTE GPRS Standard VG (Model: Voice Guide), check the micro SD card to be placed into the card holder.

Note: Never place or remove the micro SD card while the TTE GPRS Standard is powered on!

6. Switch on the main and backup power supply of the control panel.
7. Wait until the registration of the module in the available GSM/GPRS network is complete - for 60 seconds the Server Status LED will light on in red.
8. Check the signal strength - 2 or 3 RSSI LEDs are lighting on in green. If the signal strength is poor, change the location of the module or use external antenna.
9. The module is in normal operation mode - the Server Status LED is lighting on in green and the Panel Status LED is blinking in green.
10. Set the parameters of TTE GPRS Standard module using ProsTE programming software – see also item [3. Programming with ProsTE](#).

2.5 TTE GPRS Standard LED Indication

The LED indication of TTE GPRS Standard communication module has the following meaning during operation with burglary and fire alarm control panels.




1. *Server Communication Status* - LED for status of the connection between the module and AJAX SP Pro Server (or other server for monitoring).
2. *Panel Communication Status* - LED for status of the connection between the module and Eclipse panel.
3. *RSSI Signal Strength* – LEDs for the signal strength of the available GSM/GPRS network.
4. *AC LED* - Terminal for AC monitoring of CA62 and Eclipse panels only. Not used when the module is used as stand-alone device or it is connected to third-party control panels.

The LED Indication has the following meaning:

LED	Action	Colour	Description
Server Communication Status	Lights ON	Green	The module is in normal operation mode.
		Red	<ul style="list-style-type: none"> Possible trouble with the SIM card: <ol style="list-style-type: none"> The SIM card is missing. The SIM card could not register to the available GSM/GPRS network. Active PIN code for verification. No signal. Reading/Writing parameters via ProsTE software.
	Blinking	Red	Communication mode – the module transmits events over GSM/ GPRS channel.
Panel Communication Status	Blinking	Green	Successful serial connection with Eclipse panel.
		Red	No serial connection with Eclipse panel; trouble with the serial connection with the panel.
RSSI Signal Strength	●○○	Green	The signal strength is poor (from -111 to -91 dBm).
	●●○		The signal strength is good (from -90 to -70 dBm).
	●●●		The signal strength is very good (from -69 to -51 dBm).
AC	Lights ON	Yellow	No power supply 230VAC of the control panel.
	Blinking		Sending of BackUp SMS (if the option is programmed via ProsTE).

2.6 Restore to Factory Settings

This function is for restoring of the default parameters of the module set by the manufacturer.



The Reset Jumper is situated under the SIM card holder. To perform restoring to the factory settings:


1. Turn off the power supply of the module: switch off the serial interface cable from the panel.
2. Place a jumper on *RST Jumper* terminals.
3. Turn on the power supply: switch on the serial interface cable to the panel.
4. Wait for 10 seconds and remove the *RST Jumper*.
5. Wait for the *Panel Status LED* to start blinking in green.
6. Program the module with ProsTE software.

3. PROGRAMMING WITH ProSTE

ProSTE is a specialized software for programming of panels and modules produced by Teletek Electronics JSC. The installer can quickly read the current configuration, to set new parameters and to write it back to the panel or module.

Attention: Always use the latest version of ProSTE software downloaded from www.teletek-electronics.com or ask your local distributor for more information and details.


To connect the TTE GPRS Standard to a local computer or laptop for programming, use a standard USB-Micro USB data cable.




Note: The TTE GPRS Standard module must be powered up during programming and with put into place SIM card! After connecting to the computer, you may be asked to wait until the system is installing some USB drivers.

3.1 Reading a Configuration

Run the ProSTE software and choose in sequence using the right mouse button: *System – Add – TTE GPRS Standard*.



The TTE GPRS Standard menus are loaded at the left side as a tree structure. Select the module and using the right mouse button again choose in sequence: *TTE GPRS Standard – Read*.



Read is a command for downloading the current module's parameters and settings into ProSTE software.

A new window with options for *Reading* is opened:

The 'Read' dialog box is titled 'Read' and has a close button (X). It contains a tab labeled 'RS232'. Below the tab are five settings, each with a dropdown menu: 'Com Port' set to 1, 'Data Bits' set to 8, 'Parity' set to None, 'Baud Rate' set to 9600, and 'Stop Bits' set to 1. Below these settings are two icons: a folder icon and a circular arrow icon. At the bottom are three buttons: 'Ok', 'Cancel', and 'Help'.

In *Com Port* field, select the number of *USB port* to which the module is physically connected. Press OK button to continue. Next you have to enter a *PC ID code* – “1234” by default.

If the downloading is successful a message “Download from hardware finished successfully!” will appear on the screen.

3.2 General Settings Menu

Click on the “+” icon in front of *TTE GPRS Standard module* to expand the programming menus. Select *General Settings* menu. The possible settings are displayed on the right side on the screen:

The screenshot shows the software interface with the 'General Settings' menu selected. The left sidebar shows the 'System' tree with '1. TTE GPRS Standard' expanded, showing sub-items: '1. General Settings', '2. Phones', '3. Inputs/Outputs', '4. Mobile Operators', and '5. Receiver Settings'. The main area displays the 'General Settings' form with the following fields and values:

Control Panel Type	Stand Alone / None
Account Number	
Use Panel Accounts for SIA	<input type="checkbox"/>
System ID	
PC ID	1234
User Code	****
AC Delay (minutes)	1
Low DC Power Supply ,x10 mV	1140
Test Message (minutes)	20
SMS Backup Phone Number	
Software Version	9.5.1

At the bottom of the form are three buttons: 'Apply', 'Cancel', and 'Apply Selected'.

Important Note. According the used way for monitoring, there are two general approaches for programming of the **Account Number** and **System ID** fields.

- **For Monitoring stations.** Enter into the fields the specific information for the site according the used software for monitoring. See the description of the fields below.
- **For AJAX SP Pro Server.** Leave empty. The fields will be filled in automatically after the registration of Eclipse panel with TTE GPRS Standard module, or stand-alone TTE GPRS Standard, to a User account at AJAX WEB.

Description of the fields

- **“Control Panel Type”** – Choose from the drop-down list the type of the panel to which the module is physically connected:
 - **“Stand Alone/None”** – Set this option if the TTE GPRS Standard is used as stand-alone device or it is connected to third-party control panel.
 - **“CA62”** – Set this option if the TTE GPRS Standard is connected* to CA62 control panel.
 - **“Eclipse”** – Set this option if the TTE GPRS Standard is connected* to Eclipse series control panel.

Note: To be able to see the notifications and messages from TTE GPRS Standard module, you must also program in control panel engineering menus the type of the report channels. **Go to text menu “8. COMMUNICATION – 1. DIGITAL COMM – 1. OPTIONS” and set “AJAX REP. MAIN” option**, which means that the panel will report for events first through the GPRS channel (if you use address programming menus go to address 6000 and enable the option 8).

- **“Auto”** – Set this option for automatic recognition of the connected panel.

* Serial interface connection.

- **“Account number”** – This is the number of the protected site (up to 6 digits), where the system (Eclipse/CA62 + TTE GPRS Standard, or stand-alone TTE GPRS Standard) is installed.
- **“Use Panel Accounts for SIA”** (available in ProsTE version 5.3.16 and higher) – This option is used for monitoring stations only. Select the check box to enable receiving the panel account number in monitoring software using SIA-DC09 IP protocol messages.
- **“System ID”** – This is a unique name for identification (up to 15 symbols – digits, letters and special characters), between module and user in the monitoring software.
- **“PC ID”** – User access code for reading/ writing parameters to the module via ProsTE; User access code for accessing the module via AJAX WEB interface; ID number of the module. This PC ID code is special and in case of serial connection to Eclipse/CA62 panels it must be the same with one programmed into the control panel:

Panel	Text Menu	4-digit address	3-digit operation
Eclipse	8. COMMUNICATION – 1. DIGITAL COMM – 6. UDL – 2. PC ID	6901	691
CA62	-	6901	-

Important: The default set number by the manufacturer is 1234 for both module TTE GPRS Standard and Eclipse/CA62 control panel. If you need to change the PC ID code for the TTE GPRS Standard module, then you must set the same number at the respective address of the panel.

- **“User Code”** – Special security User access code for writing parameters to the module. The default code is 0000. To change it you must enter the new 4-digit code into the first field and to confirm it into the second. In case TTE GPRS Standard is used as stand-alone device, this code is used also when connecting to AJAX WEB and MobileTTE application.
- **“AC Delay (minutes)”** – This setting is important when using the module as stand-alone device only. Enter a number (0-255), for setting a time delay for “AC Lost” notification – sending a text message via Mobile TTE – for lost mains power supply. By default, 1-minute time delay is set. If “0” is set – the signalization will be immediate.
- **“Low DC Power Supply .x10mV”** – This setting is important when using the module as stand-alone device only. Enter a number (500-3000), which is the power supply threshold of the module measured in mV. When the power supply falls below this value, a message is sent to the monitoring station. Example: If you want the module to send message when the threshold falls below 11.5mV, enter 1150 in the field.

- **“Test message (minutes)”** – Enter a time in minutes (from 0 to 10080) for a time period for sending test message from the module to a monitoring station. You can disable the sending of test messages with setting “0” in the field.
Example: For sending a test message every hour, enter 60; for sending a test message every 24 hours – enter 1440, etc.
- **“SMS Backup Phone Number”** – Enter here a phone number for reporting to a monitoring station or end user. The module will send a SMS message in case of lost connection with the AJAX SP Pro Server. In case there is no need of backup SMS, leave this field empty. **Note:** It is recommended the entered phone number to start with the international calling code prefix for the country, for example “+359XXXXXXXXX”. The number can be up to 32 digits long, no spaces or special symbols are allowed.
- **“Software version”** – The current software revision of the TTE GPRS Standard module. The field is not accessible for editing.

Confirm with “Apply” button.

Quick reference table for *General Setting Menu*:

Setting	Eclipse	CA62	Stand-Alone	Third-party
<i>Control Panel Type</i>	<i>Eclipse</i>	<i>CA62</i>	<i>Stand Alone/None</i>	
<i>Use Panel Accounts for SIA</i>	✓	-	-	-
<i>Account number</i>	✓	✓	✓	-
<i>System ID</i>	✓	✓	✓	-
<i>PC ID*</i>	1234	1234	-	-
<i>User Code*</i>	0000	0000	0000	0000
<i>AC Delay (minutes)</i>	-	-	✓	-
<i>Low DC Power Supply .x10mV</i>	-	-	✓	-
<i>Test message (minutes)</i>	✓	✓	✓	-
<i>SMS Backup Phone Number</i>	✓	-	✓	-

* Default value.

3.3 Phones Menu

In *Phones* main menu are set the general options for the used phone numbers for reporting of events to user and/or for remote voice guiding. Up to 6 phone numbers can be set for operation in submenus 1-6. *Phone Number*.

Select the main menu *Phones*. The possible settings are displayed on the right side on the screen:

The screenshot displays the 'Phones' menu in the TTE GPRS Standard software. The left sidebar shows a tree view with '1. TTE GPRS Standard' expanded, and '2. Phones' selected. The main window contains the following settings:

- Enable Phone Number for Reporting:** A row of six checkboxes labeled 1 through 6, all currently unchecked.
- Enable Phone for Voice Management:** A row of six checkboxes labeled 1 through 6, all currently unchecked.
- Voice Options:** A section with a 'Skip site name' checkbox, which is unchecked.
- Voice Message Repetitions:** A numeric input field set to 3.
- Voice Communication Attempts:** A numeric input field set to 3.
- Voice Language:** A dropdown menu set to '[00] English'.

At the bottom of the window, there are three buttons: 'Apply' (with a green checkmark icon), 'Cancel' (with a red X icon), and 'Apply Selected' (with a green checkmark icon).

Description of the fields

- **“Enable Phone Number for Reporting”** – Enable the phone numbers for Reporting of events to user. “Reporting” means: receiving an SMS and/or Voice message* for event. The numbers in the field correspond to numbers of the Phones submenus: 1 correspond to submenu “1. Phone Number”; 2 to “2. Phone Number”, etc. Select the check boxes for those phone numbers, which are going to be used for Reporting.

* **Note:** The Voice messages receiving, requires your TTE GPRS Standard e to be equipped with a micro SD card with recorded voice messages from manufacturer.

Example: The Phone numbers 1, 2 and 3 are enabled for Reporting of events. The numbers 1, 2 and 3 are selected. The type of Reporting is programmed in the submenu of the respective phone number.

Enable Phone Number for Reporting						
1	2	3	4	5	6	
<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	

Enable Phone for Voice Management						
1	2	3	4	5	6	
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	

Voice Options

Skip site name ☐

Voice Message Repetitions 3

Voice Communication Attempts 3

Voice Language [00] English

Apply Cancel Apply Selected

- **“Enable Phone for Voice Management”** – Enable the phone numbers for Voice Management (Voice Guiding) by user. “Voice Management” means: remote management of the Eclipse panel by User, using the available GSM channel. The User can dial the module and to be guided by voice messages for respective operations*; or after receiving of voice message for event to switch to voice management mode. The numbers in the field correspond to numbers of the Phones submenus: 1 correspond to submenu “1. Phone Number”; 2 to “2. Phone Number”, etc. Select the check boxes for those phone numbers, which are going to be used for voice management. The full operation algorithm for Voice Management is presented in [6.3.2 Voice Management Mode – Operation Algorithm](#).

* **Note:** The Voice management mode, requires your TTE GPRS Standard to be equipped with a micro SD card with recorded voice messages from manufacturer.

Example: The Phone numbers 1, 2 and 3 are enabled for Voice Management. The numbers 1, 2 and 3 are selected. Via the set phone numbers in the submenus the users will be able to perform Voice Management of Eclipse panel (Full ARM, Disarm, Controlling PGM outputs of the panel) when they dial the TTE GPRS Standard module, or the module informs for event.

Enable Phone Number for Reporting						
1	2	3	4	5	6	
<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	

Enable Phone for Voice Management						
1	2	3	4	5	6	
<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	

Voice Options

Skip site name
☐

Voice Message Repetitions: 3

Voice Communication Attempts: 3

Voice Language: [00] English

Apply Cancel Apply Selected

- “Voice Options”** – The “Site Name” is a special voice message recorded from User with enabled Voice Management rights, up to 10 seconds long, including information for the protected site – Name, Address, Account or other.

If the “Skip site name” option is disabled (not selected) at every Reporting of event with voice message, the “Site name” message will be played first followed by the message for the event.

If the “Skip site name” option is enabled (selected) at every Reporting of event with voice message, the “Site name” message will be skipped and the user will hear only the message for the event. The recording of general “Site name” message is available in Voice Management mode – see [6.3.2 Voice Management Mode – Operation Algorithm](#).
- “Voice Message Repetitions”** – Enter a number (1-9) for a voice message repetitions. Enter 1 for single (just one time) voice message playing, 2 for twice voice message repetition and so on. The default set value is 3 (recommended). That means the voice message for event will be played 3 times as the voice message playing starts immediately after the connection with the dialed number.
- “Voice Communication Attempts”** – Enter a number of attempts (1-9) for realizing a connection with recorded phone numbers. The default set value is 3 (recommended). That means the TTE GPRS Standard will try to connect with the set phone numbers in 3 consecutive times with each of them in case the telephone line is busy (the dialed phone number is realizing other phone call at the same time) or nobody responds on the call.
- “Voice Language”** – Choose from the drop-down list the language of the received voice messages for events and the voice management.

Confirm with “Apply” button.

3.3.1 Phone Number Submenus

The user can enter up to 6 phone numbers for receiving of SMS or voice messages for events. Every phone number is set in a respective submenu. To expand the submenus, click on the “+” icon in front of main “Phones” menu. Select “1-6. Phone Number” submenu. The possible settings are displayed on the right side on the screen:

The screenshot shows the '1. Phone Number' submenu. The 'Phone Number' field is empty. The 'Messaging' dropdown is set to 'SMS'. The 'Message Type' section lists several event types with checkboxes: Alarm and Restore, Tamper and Restore, Panic and Ambush code, Fire and Restore, Arm, Disarm and Bypass, Medical Alarm, Trouble and Trouble Restore, and Special messages. The 'Message Areas' section contains a table with 16 columns (Area 1 to Area 16) and checkboxes. The bottom of the window has three buttons: 'Apply', 'Cancel', and 'Apply Selected'.

Important note: The priority of dialing of the set phone numbers starts with Phone number 1 (set in submenu “1. Phone Number”), Phone number 2 (set in submenu “2. Phone Number”), etc. The TTE GPRS Standard first will send the SMS messages and then will proceed with calls for playing the voice messages for events.

Description of the fields

- **“Phone Number”** – Enter a phone number with maximum of 32 digits. **Note:** It is recommended the entered phone number to start with the international calling code prefix for the country, for example “+359XXXXXXXX”, no blank spaces or special symbols between numbers are allowed.
- **“Messaging”** – Set the type of Reporting: SMS or Voice.
 - **“SMS”** – To the set phone number will be sent SMS messages for event.
 - **“Voice”** – To the set phone number will be transmitted calls with voice messages for events (requires optional micro SD card with recorded voice messages from the manufacturer).

Useful tip: To arrange the two types of messaging to one and the same phone number you must set the same number in two separate Phone number submenus.

For example, in “1. Phone Number” submenu, set the phone number and select the type of *Messaging: SMS*. In “2. Phone Number” submenu, set the same phone number and select the type of *Messaging: Voice*. The Phone numbers 1 and 2 must be enabled for Reporting in main *Phones* menu.

- **“Message Type”** – Select the groups of events for Reporting to User. When the “Alarm and Restore” field is selected, in case of alarm event the User will receive an SMS or voice message “Alarm” and after restoration of the zone – SMS or voice message “Alarm Restore”. Set check marks for those groups of events you want to receive as SMS or voice messages.

Note: The “Special messages” include events like resetting of the system, time changed, test, etc. The special messages are programmed in the Eclipse panel engineering menus.


- **“Message Areas”** – Select the Area numbers (in the Eclipse system) attached to this phone number. In case of an alarm event in the set Area number, the module will report to the set phone number. The area numbers depend on the used Eclipse control panel:

Control Panel	Available Areas	Message Areas
Eclipse 8	1	Area 1
Eclipse 16	3	Areas 1-3
Eclipse 32	8	Areas 1-8
Eclipse 99	16	All


Confirm with “Apply” button.

Using “Apply Selected” Button

This is a useful option for quick copying the set parameters of one Phone number submenu to another or more. When the settings of a Phone number are programmed, press the “Apply Selected” button at the bottom of the page. A new window with two sections for the all available Phone numbers submenus is opened:




Example. To copy the settings Messaging, Messaging Type and Message Areas of Phone number 1 to Phone numbers 2 and 3, select “1. Phone Number” submenu and press “Apply Selected” button. Deselect the check boxes in front of Phone numbers 4, 5 and 6. Also, deselect the check box in front of “Phone Number” setting on the right. Press “OK” button. When you check the settings of the submenus for Phone numbers 2 and 3 you will find the same settings for Messaging, Messaging Type and Message Areas as for Phone number 1, and submenus 4, 5 and 6 are left with their default or current settings without any change made. Next you have only to set different User phone numbers.



3.4 Inputs/Outputs Menu

In *Inputs/Outputs* menu the User can set the type of the TTE GPRS Standard module programmable terminals. Every terminal can be programmed as Input or Output in a separate submenu. The submenu “1.Input/Output” corresponds to terminal “IO1” of the module, “2.Input/Output” – to terminal “IO2”, and so on. By default, all programmable terminals are enabled for operation as Inputs.

Select the main menu *Inputs/Outputs*. The possible settings are displayed on the right side on the screen:




To disable a terminal, deselect the check box under it. Every number corresponds to an exact terminal on the TTE GPRS Standard PCB.

Confirm with “Apply” button.

3.4.1 Setting the Options for Inputs

The setting of a terminal for operation as *Input*, provides the opportunity for the User to receive notifications (via MobileTTE), when the input is activated. It is suitable also for monitoring station to receive the messages for events as SIA codes.

To view the submenus for terminals’ settings, double click on the “*Inputs/Outputs*” menu or expand it with clicking on the “+” icon in front of it. The same programming is applied to all terminals. Select a number from the list on the left. The possible settings are displayed on the right side on the screen:



Description of the fields

- **“I/O Settings”** – To set the terminal for operation as *Input*, choose this option from the drop-down list. (This option is set by default from the manufacturer.)
The section below is separated in two parts:
 - ❶ for setting the message for *ALARM Event*
 - ❷ for setting the message for *RESTORE Event*
- **“Enable”** – The transmitting (sending a notification) of an event can be enabled/disabled. To enable notification when the input is activated, select the check box. The deselected check box means that the sending of notification is disabled (will not be transmitted to User/Monitoring station).
- **“Alarm/Restore Event (SIA Code)”** – Choose from the drop-down list the type of the alarm event activating the input. The following settings are pre-programmed from the manufacturer as follows:


Input No	Alarm Event		Restore Event	
	Text Message	SIA Code	Text Message	SIA Code
1	Burglary Alarm	BA	Burglary Alarm Restore	BH
2	Fire Alarm	FA	Fire Alarm Restore	FH
3	Panic Alarm	PA	Panic Alarm Restore	PH
4	Tamper Alarm	TA	Tamper Alarm Restore	TH
5	Medical Alarm	MA	Medical Alarm Restore	MH
6	Arm User	CL	Disarm User	OP

- **“SMS Message (Phones)”** – Select the phone numbers (“1” for the phone number set in submenu “1. Phone Number”, “2” for the one set in “2. Phone Number”, etc) to which a SMS message for the event will be sent (see description of “SMS Message Text” field in this menu). **Important:** To avoid conflicts in reporting, you must enable only phone numbers with SMS Messaging type set in the respective submenu.
- **“Voice Messages (Phones)”** – Select the phone numbers (“1” for the phone number set in submenu “1. Phone Number”, “2” for the one set in “2. Phone Number”, etc) to which a Voice message for the event will be transmitted to the user. **Important:** To avoid conflicts in reporting, you must enable only phone numbers with Voice Messaging type set in the respective submenu.
- **“SMS Message Text”** – Editable field for SMS text report message. The user can revise the default entered text or to write a new description of the selected events. **Use only Latin small or capital letters, no special letters are allowed.**

Example. To avoid conflicts in reporting you must consider the settings for the Messaging Type made earlier in [“Phone Numbers”](#) menus for the respective phone numbers.

*For instance, when to a Phone number is set **SMS Messaging type of reporting**, the same type of reporting must be set and, in the Input/Outputs menu for this phone number – enabled check box in “SMS Message (Phones)” field.*

*When to a Phone number is set **Voice Messaging type of reporting**, the same type of reporting must be set and, in the Input/Outputs menu for this phone number – enabled check box in “Voice Messages (Phones)” field.*



Below is presented a list with all available Messages for events selectable from the drop-down list for Alarm/Restore Events.

Note: It is recommended to set only messages for Alarm event type in section ❶ and only (respective corresponding) messages for Restore event type in section ❷!

Alarm Events		Restore Events	
Text Message	SIA Code	Text Message	SIA Code
Burglary Alarm	BA	Burglary Alarm Restore	BH
Fire Alarm	FA	Fire Alarm Restore	FH
Panic Alarm	PA	Panic Alarm Restore	PH
Tamper Alarm	TA	Tamper Alarm Restore	TH
Medical Alarm	MA	Medical Alarm Restore	MH
Sensor Bypass	UB	Sensor Bypass Restore	UU
Water Alarm	WA	Water Alarm Restore	WH
Heat Alarm	KA	Heat Alarm Restore	KH
Low Temperature	ZA	Low Temperature Restore	ZH
Arm User	CL	Disarm User	OP
Arm Key	CS	Disarm Key	OS
Quick Arm	CL	-	-
Duress	HA	-	-
Communication Line Trouble	YS	Communication Line Trouble Restore	YK
AC Lost	AT	AC Restore	AR
Fire Trouble	FT	Fire Trouble	FJ


Confirm the new settings of the menu with “Apply” button.

You can also use the “Apply Selected” button if this setting has to be applied to more terminals – see [Using “Apply Selected” Button](#).

3.4.2 Setting the Options for Outputs

In case the TTE GPRS Standard module will be used for home automation projects its terminals have to be programmed as Outputs. The set Outputs can be then remotely controlled (switched ON/OFF) via [Ajax WEB User Interface](#) or [Mobile TTE smartphone application](#).


To set a terminal as an *Output*, select the respective submenu from the tree-structure on the left and choose the “*Output*” option from the drop-down list in “*I/O Settings*” section.



By default, not setting are applied for an Output. In “*I/O Settings*” section, are accessible for settings also the following fields:

- “**CLIP Deactivation (Phones)**” – Set the Phone Numbers enabled to control the deactivation (switching OFF) of the output via CLIP option*.
 - “**CLIP Activation (Phones)**” – Set the Phone Numbers enabled to control the activation (switching ON) of the output via CLIP option*.
- *Note:** “1” corresponds for the phone number set in submenu “1. Phone Number”, “2” for the one set in “2. Phone Number”, etc. The phone number is enabled when the check box is selected. It is recommended to enable both *CLIP Deactivation* and *CLIP Activation* option for a phone number.
- “**SMS Control Enable**” – Enable the controlling of the output state (switching ON/OFF) via SMS. The option is enabled when the check box is selected.


Example: Terminal 1 of the module is set as Output 1. The Phone Number 1 (set in submenu “1. Phone Number”) is enabled to switch ON (CLIP Activation) and switch OFF (CLIP Deactivation) the Output 1. The Output 1 can be also controlled via SMS messages from all set phone numbers in “Phones” menu.



Confirm the setting with “*Apply*” button. You can also use the “*Apply Selected*” button if this setting has to be applied to more terminals – see [Using “Apply Selected” Button](#).

3.5 Mobile Operators Settings Menu

Select the *Mobile Operators* menu, click on “+” icon in front of it and expand the *GPRS Settings submenu*. In the fields must be set some specific information for the mobile service provider. These fields will be filled in automatically after the registration of Eclipse panel with TTE GPRS Standard module to a User account at AJAX WEB – the user sets the mobile service provider according the selected country.



Important Note. There are two general approaches for programming of the *GPRS Settings submenu*.

- **For Monitoring stations.** Enter into the fields the specific information for the **Net Settings** of the mobile operator:

- **“Net APN”** – Enter the APN (Access Point Name) of the GPRS network.
- **“User Name”** – Enter valid user name for access to the GPRS network.
- **“Password”** – Enter valid password for access to the GPRS network.

- **For AJAX SP Pro Server.** Leave empty. The fields will be filled in automatically after the registration of Eclipse panel with TTE GPRS Standard module to a User account at AJAX WEB.

3.6 Receiver Settings Menu

This is a menu for setting the options for connection with AJAX SP Pro server. There are two sections: for *Main Receiver* and for *Backup Receiver*.

Important Note. There are two general approaches for programming of the *Main Receiver Settings* fields.

- **For Monitoring stations.** Enter into the fields the specific information for the main receiver according the used equipment and network. See the description of the fields below.

- **For AJAX SP Pro Server.** Leave the default settings. The fields for *Main Receiver* will be filled in automatically after the registration of Eclipse panel with TTE GPRS Standard module to a User account at AJAX WEB.

Note: The settings for the *Backup Receiver* must be set manually just in case of using a second backup server for monitoring.

Description of the fields:

- **“Keep Alive Message (seconds)”** – This is a time period, in which the TTE GPRS Standard module sends its status to AJAX SP Pro server to keep the communication alive. The default set period between two messages is 180 seconds, but it can be changed according the system requirements – from 20 to 200 seconds.
- **“Main Receiver”** – These are the settings for the Main Receiver Server for monitoring.
 - **“Enable Main Receiver”** – Enabling the communication with the Main Receiver server for monitoring.
 - **“Server 1 Type”** – The type of the server for monitoring: *AJAX SP Pro* or *SIA09 Receiver*. Note: For *SIA09 Receiver* the settings must be set manually.
 - **“Main Receiver Address”** – Select the type of the address for the Main Receiver server for monitoring: IP or DNS Address.
 - **“IP Address 1”** – Set the IP address of the Main Receiver server for monitoring.
 - **“DNS Address 1”** – Set the DNS address of the Main Receiver server for monitoring.
 - **“Main Receiver Port”** – The Port of the Main Receiver server for monitoring.
 - **“Encryption Key 1”** – A special security encrypted key for the connection. The key is 32-symbols long and must be set one and the same at the TTE GPRS Standard and the server for monitoring for proper operation.
- **“Backup Receiver”** – These are the settings for the Backup Receiver Server for monitoring in case of the Main Receiver failure. The settings in this section have the same description as those for the Main Receiver.

3.7 Saving a TDF File


When you complete with all parameters setting of TTE GPRS Standard, you have to save the module's configuration as TDF file. TDF (Teletek Data File) is a file format for ProsTE software.

To save the current opened module configuration, press the "Save as" button on the ProsTE ribbon bar and browse a place on your local computer.

It is recommended in one TDF file to save only one TTE GPRS Standard module configuration.

3.8 Writing a Configuration

To upload the settings from ProsTE to the TTE GPRS Standard module you have to *write* them to the currently connected module. Select *TTE GPRS Standard main menu* and choose in sequence using the right mouse button: *TTE GPRS Standard – Write*.



Write is a command for uploading the current ProsTE settings to the device configuration.

In the *Write* window select the USB port number to which you are physically connected and press *OK* button. The software will ask for a User password and PC ID code. The default codes for TTE GPRS Standard are:

- User code: 0000
- PC ID: 1234

Note: The "User code" and "PC ID" are set at General Settings Menu - [3.2 General Settings Menu](#).

A system message will inform if the writing of the new configuration in the TTE GPRS Standard module is successful.

4. AJAX WEB User Interface

AJAX WEB User Interface is a web service for monitoring of burglary alarm panels and communication modules produced by Teletek Electronics JSC. It is configured as a web application (web page) during the installation of AJAX SP Pro Cloud Server.


Ask your security provider, the monitoring company or your local distributor, whether and how you can access AJAX WEB User Interface. You can also visit www.teletek-ajax.com for review and test*.

* **Note:** All previewed examples and screens below are based on this web application.


4.1 Creating an Account

To be able to control your Eclipse burglary alarm system via TTE GPRS Standard communication module, first you must have a User account registered to AJAX WEB User Interface (hereafter referred to as AJAX WEB).

On the home page of AJAX WEB, the User must login with his personal *User Name* and *Password* or to create a new account:




To create a new account, click on “I am new user” and fill in the registration form:




Attention: It is important to enter a valid e-mail address, so to be able to complete the registration and to receive in the future the information for the registered systems to your account at AJAX WEB.

When you complete the form, press the *Register* button. You will be returned to the main home page with the following information message:



Go to your personal e-mail box and confirm the received link. The Home page of AJAX WEB is loaded automatically and in case of successful registration you will see the following confirmation message over the login section:



Then you can login the AJAX WEB.


Note: In case you receive a message for browser incompatibility, you have to proceed with registration pressing the option "Ignore and save this decision". Then, return to your e-mail box and confirm the received link again.

4.2 Adding a System to Account

After login, a system list for the User account is shown on. You will see your First and Last names from the registration form on the upper right corner of the screen. Next to it is the menu for editing your personal details.



For the new registered Users, the *System List* will be empty at the very beginning. To add a system for monitoring press *New Module* button on the right.



A new window "New Module Registration" with addition information for describing the security system is opened.

In case of serial connection between *Eclipse panel* and *TTE GPRS Standard module* you have to make the following settings:

- **“System Name”** – Enter a name describing the protected site. The name can be edited or changed later.
- **“Panel”** – Select **Eclipse** type from the drop-down list.
- **“Type of connection”** – Select **GPRS** type from the drop-down list.
- **“Country”** – Select from the drop-down list the country of the mobile operator.
- **“Mobile operator”** – According the selected country you must select the mobile service provider.
- **“Attach TDF File”** – Click on *Browse* and select the preliminary saved TDF file of the TTE GPRS Standard module’s configuration.

Security system: Eclipse + TTE GPRS Standard module.

Select your country and mobile service provider*.

In case of using *TTE GPRS Standard module as a stand-alone device* or *it is connected to third party panel* you have to make the following settings:

- **“System Name”** – Enter a name describing the protected site. The name can be edited or changed later.
- **“Panel”** – Select **Standalone** type from the drop-down list.
- **“Type of connection”** – Select **GPRS** type from the drop-down list.
- **“Country”** – Select from the drop-down list the country of the mobile operator.
- **“Mobile operator”** – According the selected country you must select the mobile service provider.
- **“Attach TDF File”** – Click on *Browse* and select the preliminary saved TDF file of the TTE GPRS Standard module’s configuration.

Using the module as stand-alone device, or in case of connection to third-party control panel.

Select your country and mobile service provider*.

*** Important Note:** If the used mobile operator is not present in the list, choose any other, just to complete the registration. Then after [loading the service TDF file in ProsTE software](#), you must enter the exact settings in [Mobile Operators](#) menu and then write into the TTE GPRS Standard module.

Confirm with *Register* button.

In a new window is presented summary information about the new system registration:


New module registration

You will receive an email with instructions and settings for your device.

Please set your device with the following parameters

Primary IP	78.130.143.82
Primary Port	37000
System ID	123456@#\$999504
Encryption key	3A414AE6E14019F659AD28513EC925F8
Account number	999504
Operator APN	globul1
Operator username	globul1
Operator password	globul1

Use the following QR code to register in MobileTTE



[Get TDF](#) [Close](#)

All this information is loaded in a service TDF file which is sent to your personal e-mail address (those you have been provided for the account registration).

This is the service information for the Mobile Operator in [Mobile Operators Menu](#) of ProsTE software. It is different and depends on the selected country and the mobile operator.

This is a special QR code for directly adding the system information to MobileTTE smartphone application.

You can also directly download the service TDF file for the security system and save it to your local computer.

Press “Get TDF” button and download the service TDF file containing the pre-programmed information for the module, mobile operator and the automatically set parameters for the connection with AJAX SP Pro server (in ProsTE - [“Receiver Settings” menu](#)).

Press *Close* button to exit the *New Module Registration* window.

At this stage your system is added to the *System list* but it is still offline, because the settings for the connection with AJAX SP Pro server are not set to the TTE GPRS Standard module yet.

Filter by: <input type="text" value="System name"/>					Set Filter	New Module
Online	System name	Account	Type			
<input type="radio"/>	Office	999504	Unknown panel	Status	Offline	Edit Delete Share

Important note:

Every new added system must be connected (to become online) to the AJAX SP Pro server in 24 hours after the registration. That means the TTE GPRS Standard module to be programmed with the received service TDF file and connected to an available GPRS network. If, 24 hours after the registration there is no online connection between the module and the server, the registration will be automatically deleted and the Account number will be free for other new registration.

4.3 Online Connection with AJAX SP Pro Server


After the successful adding of the new registered system to the User account, the TTE GPRS Standard must be programmed with the service TDF file generated during the registration.

Open ProSTE software and connect your local computer to the TTE GPRS Standard using standard USB – Micro USB data cable. Press *Load* button on the main ribbon bar and open the downloaded earlier service TDF file for your registered system. Click on the “+” icon in front of *System* to expand the menus of TTE GPRS Standard module. You can review the *General Settings*, *Mobile Operator* and *Receiver Settings menus*. There will be available the automatically set parameters from the server. You can edit some of them if necessary.

Select in sequence using the right mouse button *TTE GPRS Standard – Write* to upload the settings into the module. Follow the steps as described in item [3.8 Writing a Configuration](#).

When the uploading is complete, go back to the AJAX WEB and login into your account.


If the online connection is established, the system will be now online, the type of Eclipse panel to which the TTE GPRS Standard module is connected will be recognized and visible, and the system will be ready for remote management and control by user.



Important note: If a system operates for a while, and for some reasons becomes offline, the server will keep it in the system list up to 30 days after the disconnection. After that period the system will be deleted automatically.

4.4 Operation with System

The User can perform some operation with the systems added to his account.



- **“Search Filter”** – On the top of the *System List* section, the User can search among the added systems to his account filtering them by: *System Name*, *Status (Online/Offline)*, *Account number* or *Type of the control panel*. Choose from the drop-down list the option for filtering and enter into the second field word or value for searching. Press the *Set Filter* button to start.
- **“New Module”** – Adding new system to the User account – see item [4.2 Adding a System to Account](#).
- **“Status”** – Click on the button to review some information about the connection between the system and the server – the system status. In the new window you will find

details about the date of registration, last communication and the last user login for management and control.

System status:	
Register on:	21 Nov 2019, 2:02:48 PM
Last communication with server:	22 Nov 2019, 12:38:36 PM
Last client login:	22 Nov 2019, 12:37:51 PM
<input type="button" value="Close"/>	

- **“Connect/Busy”** – Remote control of the system and management of the control panel state (ARM, DISARM, ZONE BYPASS, etc.), management of the TTE GPRS Standard outputs, review the memory log and the status of the zones. The available operations depend on the user rights assigned in the control panel.


Attention: Every system can be shared for operation between different users, but only one of them can access it at a time. If the system is accessed from a User, the button becomes inactive with text “Busy”. That means the system is not accessible for control from other users at this time.

The system is accessible when the button “Connect” is visible and active. To connect to the system, press the button and enter the *PC ID Number* (1234 by default) and a valid user code for the respective control panel. If you are using the TTE GPRS Standard as a stand-alone device, enter the security User code set with ProsTE – see also item [3.2 General Settings Menu](#).

- **“Edit”** – Editing the name of the system and setting the type of notification messages for events received via MobileTTE. Press the button to open the window for editing:

Device settings

Device name



You can use the QR code at any time for scanning and directly adding the system information to MobileTTE smartphone application.

Here you can change the name of the system.


	Red Dot Notifications	Push Notifications
Alarm & Restore	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
Arm, Disarm, Bypass	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
Fire & Restore	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
Medical Alarm	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
Panic & Ambush code	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
Special Messages	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
Tamper & Restore	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
Trouble & Restore	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>

These are special sections for setting the notification messages received via MobileTTE.

- **“Red Dot Notifications”** – A special mark (a red dot) alerts the User in case of occurring of an event (in the system list of MobileTTE). Check the boxes of those events for which you want to be alerted. See [Red Dot Notifications](#) in the User Guide.
- **“Push Notifications”** – Check the boxes for those events for which you want to receive a push notification messages on your smartphone. See [Push Notifications](#) in the User Guide.
- **“Delete”** – Deleting the system from the list and from AJAX WEB. The site will ask for confirmation. **Note:** Once deleted from the list and from the AJAX WEB, the system could

not be restored again. If you delete it by mistake, you have to add the system again following the steps described in [4.2 Adding a System to Account](#).

- **“Share”** – Sharing the access to a system between two or more different users. To share the access, you have to know in advance the account Usernames of those Users to which you want to assign rights for operation. Press the “Share” button to open the “User Assignment” window.




Step-by-Step Example for sharing access to a system:

1. Enter in “User name” field a real account Username registered in AJAX WEB.
2. Press “<<Add” button.
3. The name of the User will be added to the list of the Assigned Users.
4. Press “OK” button.

To remove a User from the List, select it and press “Remove>>” button. Then confirm with “OK”.

The shared system is added automatically to the user account, but without the option for sharing (for account “user5120” from the example above):




Note: The right to share a system for operation with other users, can only the User who is performed the New Module Registration procedure (the initial registration of the system) to his own account.

5. TTE GPRS Standard – Installation Summary

Here is a short list of the important steps necessary for successful connection of TTE GPRS Standard module to AJAX WEB.

- Check the control panel to which you are going to connect the TTE GPRS Standard communication module. The module is your “online” connection for remote management and control of your Eclipse burglary alarm control panel. In case the module is used as a stand-alone device it is necessary to power it on with an external power unit 9-30VDC. See also item [2.1 Serial Connection](#).
- Disable the PIN protection code of the SIM card for the module and place it in the holder. For TTE GPRS Standard VG (Model: Voice Guide) check the micro SD card to be placed into the SD card holder.
- Using the serial cable, connect the module to the Eclipse panel. Power on the Eclipse control panel.
- [Read](#) the Factory setting of TTE GPRS Standard and pre-program the [panel type](#), [phone numbers](#) for Reporting and [inputs/outputs](#).
- [Save](#) this configuration (FileName.TDF) on your local computer or laptop. You will need this file later during adding the system to AJAX WEB.
- Open AJAX WEB site and login. If you are a new user - [make a registration](#).
- In the system list of your account press “New module” button and [register](#) your security system (Eclipse panel + TTE GPRS Standard) or module (stand-alone TTE GPRS Standard).
- [Save the service TDF](#) from the registration form on your local computer or laptop.
- Open ProTE software, connect to TTE GPRS Standard and [write](#) the service TDF file received from AJAX WEB.
- The established connection with AJAX WEB is indicated with permanently lighting of the green LED “Server State” of TTE GPRS Standard communication module. The Online status of the system will be indicated with an active online status (green) after login the AJAX WEB.



6. USER GUIDE


6.1 AJAX WEB User Interface

Using AJAX WEB interface, the user can perform remotely the following activities with his security system and TTE GPRS Standard module:

- review the current status of the areas, troubles and the memory log of the control panel and the connected TTE GPRS Standard module;
- to Arm, Disarm, Bypass Zones of the control panel;
- to control and to review the status of the PGM outputs of the control panel;
- to control and to review the status of the PGM outputs of TTE GPRS Standard module;
- to edit system parameters (managers only).

6.1.1 Remote Access

Login in your AJAX WEB User account and press “Connect” button next to the system.



The site will ask for *PC ID Number* (1234 by default) and a valid user code for the respective control panel. **Note that, the performed remote actions with the panel depend on your assigned user right for operation in the security system.**

The screenshot shows the 'Connect the System' dialog box. It contains a text area explaining that the UDL number is a password for remote access. Below this, there are two input fields: 'PC ID number' and 'User code', both with masked characters (dots). These two fields are highlighted with a red box. At the bottom, there are 'Cancel' and 'Connect' buttons.

Press “Connect” button and wait until the connection with the system is established.


6.1.2 Main Menus

The online connection with the system provides a range of activities for the User (according to his assigned rights in the control panel).

The main menus are located on the top:

- **System Status.** The User can review and control the Eclipse control panel connected to TTE GPRS Standard module. The menu has 4 additional submenus – see item [6.1.3 System Status](#).
- **Edit Parameters.** The access to this menu is limited for Users with manager rights in the system only.
- **View Events.** Downloading the memory log file of the panel – see item [6.1.4 View Events](#).
- **Communication Module.** Control of the TTE GPRS Standard module Outputs – see item [6.1.5 Communication Module](#).

The unavailable menus are presented into grey; the available – into blue; and the current selected – into black colour.



To exit from the system press “Disconnect” button.

6.1.3 System Status

This menu is about the connected Eclipse control panel. The User will see on the screen the areas and zones with which he has rights to operate.

Troubles & Areas Control Panel Submenu

The screen is divided into three sections:

The screenshot shows the 'Office: SYSTEM STATUS' screen. The top navigation bar is the same as in the previous image. Below it, there are tabs for 'Troubles & Areas', 'Zones', 'Control Panel PGMs', and 'IP Cams', with a 'Refresh' button on the right. The 'Troubles & Areas' tab is selected, showing three sections:

- Troubles** (labeled 1): A section for reviewing current technical troubles. It shows a red circle icon and the text 'Sysbus error'. A note states: 'Section for review the current technical troubles. This section is hidden if there are no troubles or faults. The presented troubles are restored automatically when fixed.'
- Areas** (labeled 2): A section for managing the arming state of areas. It shows a table with columns for area name, status, and action buttons. The current state is visible with an icon and text description.

Area	Status	Full	Stay	Sleep	Disarm
All areas	Disarmed	Full	Stay	Sleep	Disarm
Area 01	Disarmed	Full	Stay	Sleep	Disarm
Area 02	Disarmed	Full	Stay	Sleep	Disarm

 A note states: 'Section for managing the arming state of areas. The current state is visible with icon and text description.'
- System Time** (labeled 3): A section for setting the actual current time and date. It shows a date field (27 Nov 2019), a time field (04 : 51), and a 'Set New Time' button. A note states: 'Section for setting the actual current time and date.'

Every action in the “Troubles & Areas” submenu requires entering a valid user code for confirmation.

You can use only your personal access code – the one with which you are connecting with the system.








You can also refresh the presented information at any time with the “Refresh” button.

In **Section 1**, the user can review the technical troubles:


Trouble	Description
AC Loss	The mains power supply is lost.
Battery Low	The accumulator battery is discharged or missing.
Blown Fuse	Blown out fuse on the control panel.
Communication trouble	Telephone line (PSTN) or digital communicator (GPRS) is lost. Communication with central Monitoring station fails. Sending of message (PSTN/GPRS/LAN) is impossible.
Tamper	Open tamper in the system.
Sysbus err	System bus error. It could be short circuit in the line or lost device.
Fire line Error	Fire Detector Loss or the fire line is broken.
Siren Fault	Problem with connected siren; no siren connected to PGM5.
Invalid clock	The internal clock has to be set to an actual time and date.
WL device trouble	Possible problems: - Low battery charge of wireless device; - Wireless device lost; - Dirty chamber of a wireless fire detector.
WL RF jamming	Radio signal jamming.
AUX PSU trouble	Possible problems with power supply of expander modules: - The mains power supply is lost; - Problem with the backup battery; - Blown out fuse.

All troubles are restored automatically when fixed.

In **Section 2**, the user can change the arming state of area just pressing the respective button for Full, Sleep or Stay type arming. The current state is presented with color icon and text description next to it. Other events, like Burglary alarm or Memory, can be also viewed for the respective area according the current situation.


Icon	Text	Description
	Disarmed	The Area is disarmed. The User can perform Full, Stay or Sleep Arm; to bypass zones; to control the PGM outputs of the control panel and TTE GPRS Standard.
	Not Used	The Area is not used in the system.
	Exit Time	The exit time for leaving the protected Area is running on.
	Entry Time	The entry time for the protected Area is running on. That means an entry-exit type zone is opened and the system is waiting for entering a valid user code via keyboard or proxy reader (installed in the protected site).
	Full Armed	The Area is Full Armed. All attached zones are secured.
	Stay Armed	The Area is in Stay Arm security mode. Some zones inside it are disarmed. The armed entry-exit type zones will initiate entry time running after opening.
	Sleep Armed	The Area is in Sleep Arm security mode. Some zones inside it are disarmed. The armed entry-exit type zones will initiate immediate burglary alarm after opening.

In **Section 3**, at the bottom of the page, the User can update the time and date of the control panel. To set the Date, press on the calendar icon and choose the “Today:...” option. To set the time [HH:MM], enter the current time into the next field. Confirm the new settings with “Set New Time” button. The site will ask for valid user code for confirmation.



Zones Control Panel Submenu

To review the available zones in the Eclipse system, press “Zones” tab in *System Status* menu.



The available for operation zones are with active buttons for Bypass/UnBypass options. The User can review the current actual state as the action is shown with an icon in the respective column.

The button “Camera” is visible for zones with attached [IP cameras for video surveillance](#).

Note: The “Battery” column refers to zones with attached wireless devices only.

The Bypassing and UnBypassing of zones can be performed only when the system is disarmed. The site will require entering a valid user code for confirmation.

Icon	Description
	No movement in the Zone.
	Movement in the Zone.
	No active tamper in the Zone.
	Active tamper in the Zone.

Icon	Description
	No alarm in the Zone.
	Alarm in the Zone.
	No memory event in the Zone.
	Memory event in the Zone*.


* You can check the type of the memory event in [“View Events” main menu](#).

Control Panel PGMs Submenu


To review the available PGMs in your Eclipse panel, press “Control Panel PGMs” tab in *System Status* menu. The available PGMs for control depend on the settings programmed in your Eclipse security system. **Note: The PGMs are active for remote control only when they are programmed with option “Remote Control” (ask you installer or security provider for more information).**

The PGMs can also be programmed to be activated from an event in the system.

The User can set a specific name for every PGM in order to recognize them easily. The set names can be edited at any time.



The remotely controlled PGMs can be turned ON/OFF using the button next to their number. The action is confirmed with entering an active user code.




The PGMs states:

Icon	Description
	The PGM is turned OFF (deactivated) or it is not used.
	The PGM is turned ON (activated).

IP Cameras Submenu

This is a special menu for attaching IP cameras for video surveillance to security zones in the protected site. The IP cameras must support operation via RTSP communication protocol. This is an opportunity for the user to watch a live video from the site directly via AJAX WEB without using other video application software for monitoring.

To attach a camera, first press “New Camera” button on the left side.



In a new opened window, the User has to choose the Camera Properties.

“Camera Type” – Choose from the drop-down list the type of video device - IP camera or NVR recorder.

“Camera Name” – Enter a specific name for the attached camera.

“Zones” – Select the zone numbers to which the camera is attached. You can select more than one zone number as press and hold the “Ctrl” button on the keyboard and select the zone numbers with the left mouse button. Also, you can attach more than one camera to a zone number.

Press “Next” button to continue.



Depending on the set *Camera type* video device, a window for setting the connection between the security camera and AJAX WEB is opened.

You must follow the given instructions on the screen:


IP Camera	NVR Recorder
<ol style="list-style-type: none"> Set the parameters from your IP camera in the required fields. Open the camera settings menus and choose in sequence: Configuration->Network->Port Select the “SD Card” field to enable the option for backup recording on a SD card. Get the parameters for the connection with AJAX WEB and set them into your IP camera programming menus: Configuration -> Basic Settings -> DDNS 	<ol style="list-style-type: none"> Set the parameters from your NVR recorder in the required fields. Open the NVR settings menus and choose in sequence: Configuration->Network->Port Select the channel number (the number of the camera connected to your NVR). Enter a specific name for the NVR recorder. Get the parameters for the connection with AJAX WEB and set them into your NVR recorder programming menus: Configuration -> Basic Settings -> DDNS

Press the “Save” button to add the IP camera to the list.

All added video devices are presented in a list in *IP Cams* menu with their online status:

Icon	Description
	The IP camera is offline. No video streaming is available.
	The IP camera is online. The User can watch the live video streaming in “Zones” menu.

In “*IP Cams*” menu the User can also edit and delete the attached cameras to zones. The cameras connected to an NVR recorder are presented with the name of the recorder (in column NVR).




Stand-alone IP cameras.

IP Camera connected to NVR.

6.1.4 View Events

The User can retrieve and review the memory log file of the Eclipse control panel at any time, irrespective of the arming state. To retrieve the log memory, press the “*View Events*” main menu, enter a valid user code and press “*OK*” button.



Search filter section – choose the search options and press “*Filter*”.

List of the events. The newest event is shown on top, as in the list are retrieved the last 20 events in the system.

Press “*More*” to retrieve the next 20 events.



Note: Retrieving of all memory events may take some time according the number of records.

Use “*Print All*” button to print the currently retrieved memory events on the screen.

6.1.5 Communication Module

In this main menu the User can review the type of the programmable inputs/outputs and to control the outputs of TTE GPRS Standard communication module. The terminals of TTE GPRS Standard are programmed in advance as inputs or outputs via ProSTE software – see item [3.4 Inputs/Outputs Menu](#).

The TTE GPRS Standard outputs states:

Icon	Description
	The output is turned OFF (deactivated) or it is not used.
	The output is turned ON (activated).







The current information for all 6 terminals of TTE GPRS Standard is displayed as the User can review their set type – output or input. The outputs are remotely controlled with Turn ON/OFF button. The User can set different names for every of the inputs/outputs according their functionality in the system.

The remote control of the outputs can be done at any time, irrespective of the arming state of the control panel.

[System status](#) | [Edit parameters](#) | [View events](#) | **Communication module** [Disconnect](#)

Office: Communication module

PGM's

PGM No		Type	Active	
1	Lighting Edit name	Output		Turn Off
2	Tamper Edit name	Input		
3	AC loss Edit name	Input		
4	Set name	Input		
5	Set name	Input		
6	Set name	Input		

To activate the PGM output, press once the “Turn ON” button next to it. The status becomes “Active” and the button is changed to “Turn OFF”.

To deactivate the PGM output, press once the “Turn OFF” button. The status becomes “Inactive” and the button is changed to “Turn ON”.


6.2 Mobile TTE Smartphone Application

Mobile TTE is a smart phone application suitable for remote management of burglary control panels and modules produced by Teletek Electronics JSC. The application is compatible with Android and iOS platforms and can be downloaded directly from Google Play and App Store, or you can use the provided QR codes below:



6.2.1 Adding a System to Mobile TTE

Run the Mobile TTE application and Press *Menu – Add System*.




Then you have to choose the way of adding the system. You can add the information manually or to scan the [QR code](#) received after registration of the system in AJAX WEB (recommended).

Choose the button to add the settings for system manually.

You will be asked to enter:

- your account username and password in AJAX WEB;
- a system attached to your AJAX WEB account;
- UDL (PC ID) code (1234 by default).




Open the e-mail from the registration of the system and scan the received QR code.

The system will be added to the *System List* of MobileTTE. If the system is online and ready for operation that will be displayed with text in green. If there is a red dot in the upper left corner, that means there is a system event (the [red dot notifications](#) are set in AJAX WEB user account for every of the attached system and also can be edited in MobileTTE Settings Menu).


6.2.2 Connection to a System

To connect with the system, press the button and wait until the connection is established. When you are connecting to a system for the first time you will be asked to enter your valid user code for operation with Eclipse panel, or in case the TTE GPRS Standard is used as stand-alone device, the security user code set with ProsTE – see item [3.2 General Settings Menu](#).




6.2.3 Operation menus in MobileTTE

According the assigned user rights to your code, you will be able to operate remotely with the Eclipse panel and/or the TTE GPRS Standard module (stand-alone device).




6.2.4 Controlling of PGMs

Press *Outputs* menu. Via MobileTTE the user can review and control only the enabled for remote control PGM outputs for the Eclipse panel and TTE GPRS Standard module. The outputs are presented with their names set in AJAX WEB, as the PGMs in Eclipse panel are described as “Panel” and those in TTE GPRS Standard are described as “Module”. The status of the output is changed with pressing ON/OFF button.




6.2.5 System Main Menu

There are some important settings for the system. After connection press “Menu” button in the right upper corner of the screen. Then choose *Settings*.




The general functions of MobileTTE is to provide to the user remote control of his Eclipse control panel and the outputs of TTE GPRS Standard communication module, receiving of notification messages in case of alarm or trouble events and the arming status of the system.

The receiving of notification messages is disabled by default. The enabling of this function is in the *Settings* menu of the respective system.



The receiving of notification messages is enabled when the “*Enabled*” setting is visible in the section.

In this menu the User can also set the type of the events for which to receive notifications. Select the *Push Notification Groups* and select those type of events for which you want to be informed.




By default, all types of events are enabled (it depends also of the settings in AJAX WEB). The number of set notifications will be visible on the screen.

The notifications have the following description:

Event	Description	Sound type
ALARM	Notification in case of burglary alarm in the system.	Special alarm tone*
ARM	Notification in case of arming (Full, Stay, Sleep) and disarming.	General notification tone
FIRE	Notification in case of fire alarm in the system.	
MEDICAL	Notification in case of medical alarm in the system. (Activated medical type zone or panic button.)	
PANIC	Notification in case of panic alarm in the system. (Activated panic type zone or panic button.)	
SPECIAL	Notification in case of other special events in the system like resetting of the system, time changed, test, etc. The special messages are programmed in the Eclipse panel engineering menus.	
TAMPER	Notification in case of open tamper in the system (panel or device).	
TROUBLE	Notification in case of trouble or fault event in the system.	

***Note:** Some smartphone models do not support the second alarm tone for notifications. In case the receiving of notifications is enabled, but you do not receive them, is necessary to check your smartphone settings and to enable also the notifications from installed applications programs.


In *Settings* menu the user can also set the visualization of events via red dot in the system list. Select the *Red Dot Notification* and select those type of events for which you want to be informed.



You can find the description of the events in the table above.

It is recommended to leave the default settings for *Refresh time* and *Last events* because they are optimal for the application.


Move down to the bottom of *Settings* menu. There are options for setting the date and time of your control panel and to select different language of your MobileTTE smartphone application.



Optional setting of the time and date in your control panel.

Change the language of the MobileTTE application menus.
Note: This setting will not affect the set names of Areas, Zones and PGMs in the system.

The other option in *Menu Settings* of the system is to clear or change the user code for access to control panel.



The “*Clear Code*” option will delete the current set user code for access and during the next connection of the system the application will ask for entering of valid user code.

The option “*Change Code*” is used to set a new code for access to the application. In the new screen you will be asked to enter your current code, the new code and to confirm the new code again.

Attention: In case a message for changing code error is shown, the probable reason may be that you are trying to change a regular user code with manager's one! Ask the installer of your control panel about the users and managers access codes in your security system.


In case you are using the TTE GPRS Standard module as a stand-alone device you must use only the security user code programmed with ProsTE – see item [3.2 General Settings Menu](#) .

To exit from the system, back to the main system list, press *Disconnect* button. The currently installed version of MobileTTE on your smartphone is reviewed with *About* button.

To exit from MobileTTE application press the *Back* button of your smartphone.

6.3 Voice Management

The Voice Management is an optional mode for remote control of Eclipse series panel via the TTE GPRS Standard module through the available GSM communication channel. The User can dial the TTE GPRS Standard and following the played voice guiding messages to control the arming state of Areas in the control panel (Full ARM and DISARM), to control (switch ON/OFF) the PGMs of the control panel and also to record the general message for the site – the “Site Name” message.



The Voice Management requires a micro SD card with recorded voice messages from the manufacturer. The micro SD card is included in the kit of TTE GPRS Standard VG (Model: Voice Guide).

6.3.1 Receiving of Voice messages for Events

In case of alarm or trouble event in the system, the TTE GPRS Standard will dial the entered phone numbers with set Reporting type option “Voice” (see [3.3.1 Phone Number Submenus](#)) and will play a voice message about the Type of Event, the associated to this phone Area number and Zone number.

For example, the format of the message for burglary alarm in Zone 2 attached to Area 1 will be:


“<Area 1> <Alarm> <Zone 2>”,

and the TTE GPRS Standard will dial just those phone numbers associated to Area 1 (see [3.3.1 Phone Number Submenus](#) – Message Areas section).

If several events are occurred in sequence, the module will play the respective voice messages for them one by one. The voice messages can be played one or several times, according the setting for “Voice Message Repetitions” in ProsTE software (see [3.3 Phones Menu](#)). After the last message, two system messages are played:

- “To confirm, press pound (#)” – The user can confirm the receiving of the messages with pressing the “#” button and to cancel the call.
- “For system control, press 1” – The user can switch directly to voice management mode.

6.3.2 Voice Management Mode – Operation Algorithm



Note: When operating with Eclipse 8, the messages for entering of Area number are missed and the user has not to enter an Area number. When operating with Eclipse 16 the correspondence of the Areas is as follows: Area 1 (A), Area 2 (B) and Area 3 (C).


6.4 SMS Messages for Events

In case of alarm or trouble event in the system, the TTE GPRS Standard will send SMS messages to those phone numbers with set Reporting type option “SMS” (see [3.3.1 Phone Number Submenus](#)). The type of the message group (Alarm and Restore, Tamper and Restore, etc) are set in advance.

If several events are occurred in sequence, they will be sent as a list in one SMS in the order of occurring. Every message is including information about the Type of Event, User, Area and Zone number according the event.

The remote control actions, performed via Mobile TTE and AJAX WEB application, are described with “Remote” text in the SMS message.

Examples.



Note: “User 1” in the presented examples, is a name and means that the action is performed with an access code associated to user with this name set in the Eclipse panel. According the programming of your Eclipse panel, to the different users can be set different names which are going to be displayed in the content of the SMS message.

6.5 Operation via Mobile Phone

To be able to control and to perform actions with the outputs of TTE GPRS Standard module, the used phone number must be set and enabled for operation in advance at the submenus “Inputs/Outputs”. The options for CLIP and SMS control must be enabled (see [3.4.2 Setting the Options for Outputs](#)).


Important Note: For the remote commands use capital or small Latin letters and digit numbers only. No special symbols or letters are allowed! You must use only the exact commands presented in the following items description.

6.5.1 Remote Resetting of TTE GPRS Standard

This is an option for remote resetting of the module via SMS command. To perform Restart of the module, send an SMS to it with text “Reset” or “Restart”. The module will confirm the received command with message “Module will restart after 10 seconds”. After resetting the module will send another message - “Power UP” - confirming the resetting has been done.

If the message “Error: Invalid syntax” is received, that means the sent command is not typed correctly or there is used a special symbol or letter in the text.

Example:



6.5.2 Checking the Signal Strength

This is an option for checking the signal strength of the used GSM network. The signal strength is presented in “-XX dBm” format. The strength depends on the measured value of the signal in [dBm]:

Range	Signal strength	Possible problems
-111 dBm to -91 dBm	Poor	Dropped calls; signal may break up.
-90 dBm to -70 dBm	Good	Signal may break up.
-69 dBm to -51 dBm	Very good	-

To check the signal strength, send an SMS to the module with text “Rssi”. The module will return back an SMS with a measured value.

Example:



If the message “Error: Invalid syntax” is received, that means the sent command is not typed correctly or there is used a special symbol or letter in the text.

6.5.3 Changing State of PGM Outputs via CLIP

This option is only for the set PGM Outputs of the TTE GPRS Standard module. With every single calling to the module, the user changes the current state (ON to OFF or vice versa) of the PGM outputs enabled for operation with the respective phone number. To change the current state of the PGM Output(s) simply call the module and wait for one ringing tone. Then cancel the call.

Attention: If you wait longer, for two or more ringing tones, the module will answer the call and will enter into Voice Management Mode. But even in that case the PGM Output(s) will change their current state if the CLIP control is enabled for the respective phone number.

6.5.4 Changing State of PGM Outputs via SMS

This option is only for the set PGM Outputs of the TTE GPRS Standard module. The user can switch ON/OFF the PGM Outputs one by one pointing their exact number.

To perform changing of the PGM Output state, send an SMS to it with text:

“Output X on” (for switching the Output ON), and

“Output X off” (for switching the Output OFF).

In confirmation of the performed operation, the module will send an SMS message, as follows:

“Output X is On” (the Output has been switched ON), and


“Output X is Off” (the Output has been switched OFF).

The “X” is a number of the respective PGM Output from 1 to 6.

The user can receive also the following messages for errors:

Message	Description	Solution
<i>“Error: Invalid Output Number - X”</i>	The entered Output number is wrong, not existing. The PGM output numbers can be from 1 to 6.	Enter a correct PGM output number from 1 to 6.
<i>“Error: PGM Number X is Input”</i>	The current setting of the entered PGM number is for Input.	To use the respective PGM number as output you have to change the setting with ProsTE software. See 3.4.2 Setting the Options for Outputs .
<i>“Error: PGM Number X is Not Allowed”</i>	Currently the operation via SMS commands with the respective PGM number is disabled.	Enable the operation via SMS commands for the respective PGM number. Select the “SMS Control Enable” check box in menu 3.4.2 Setting the Options for Outputs .
<i>“Error: Invalid syntax”</i>	The sent command is not typed correctly or there is used a special symbol or letter in the text.	Check the entered command and type it correctly.

Example:





www.teletek-electronics.com

Address: Bulgaria, 1407 Sofia, 14A Srebarna Str.

Tel.: +359 2 9694 800, Fax: +359 2 962 52 13

e-mail: info@teletek-electronics.bg
