



# GFE-BCM-3

## PSU with Battery Charger Module



This unit is a fully EN54-4 compliant PSU incorporating a battery charger that can be used with all of GFE's addressable and conventional panels. It will monitor all fault conditions including: charger fault, charger voltage level, input voltage supply fault and supply removal. It is supplied boxed in an ABS plastic enclosure, including a 28V DC @ 1.7 or 2.4 Amp PSU.

### KEY FEATURES

- Battery charger monitored
- Fault relay output
- Low battery voltage shutdown
- Reverse polarity protection
- Battery charger current regulated
- LED indicators: AC ON, Battery & Charger Fault
- Boxed unit inc. PSU and battery compartment
- Fully compliant with EN54-4

### TECHNICAL SPECIFICATIONS

SUPPLY INPUT	230 +10% -15% V AC - Monitored
SUPPLY OUTPUT	1.7 A OR 2.4 A @ 28V DC nominal
BATTERY CHARGER - CURRENT O/P	1 A max.
BATTERY TYPE	Max. 2 x 12 V 7 AH - Lead Acid VRLA
BATTERY FUSE	3 A
FAULT RELAY	Changeover - 30V DC 1 A Resistive
OPERATING TEMPERATURE	-10°C to +50°C
HUMIDITY	Max. 95% no condensation
PROTECTION	IP21
DIMENSIONS	273 (L) x 107 (W) x 404 (H) mm
WEIGHT	1.7 Kg - 7 Kg inc. 2 x 7 AH Bat.

### ORDER CODE

GFE-BCM-3 (1.7 A)	BATTERY CHARGER MODULE - 28V DC 1.7 A PSU - BOXED
GFE-BCM-3 (2.4 A)	BATTERY CHARGER MODULE - 28V DC 2.4 A PSU - BOXED

© March 2021

#### Global Fire Equipment SA

Sítio dos Barrabés, Armazém Nave Y, Caixa Postal 908-Z  
 8150-016 São Brás de Alportel. PORTUGAL

Telephone: (00351) 289 896 560 / Email: info@globalfire-equipment.com / Web: www.globalfire-equipment.com



**GSS GROUP**