

# Eclipse LED 16

## LED Keypad

### Description

LED 16 is a keypad with LED indication of zones, system troubles, alarm messages and arming type. It is part of the ECLIPSE series alarm systems. The keyboard provides 1 input zone. LED 16 is suitable for programming and management of systems up to 2 independent areas and up to 16 zones.

### Technical Specifications

Power Supply from the control panel . . .	9-18V (nom. 14V)
Consumption . . . . .	Min. 50mA / Max. 80mA
Area Indication . . . . .	2
Zone Indication. . . . .	16
Panic buttons . . . . .	Yes
Buttons . . . . .	Rubber
Operation temperature . . . . .	-20 ÷ +50°C
Tamper . . . . .	Yes
Dimensions . . . . .	100x90x24mm



### Functional Specifications

- Shortcut buttons to additional menus – Memory, Troubles display and Bypassed zones;
- Quick buttons for all arming modes;
- 3 fast buttons' combination for sending of PANIC, MEDICAL and FIRE alarm messages to a central monitoring station;
- The system parameters can be fully programmed;
- Supports 2 programming types: 4-digit addresses and 3-digit operations;
- Adjustable intensity of backlight for the display and buttons;
- Adjustable sound volume of the internal buzzer.

### Packing Information

- **Master box** - 80 units LED 16, dimensions 496 x 305 x 206 mm

### Compatible Product Range

- **Eclipse 8** - Alarm Control Panel
- **Eclipse 32** - Alarm Control Panel

### Contact Information