

PM861

Power Supply Switch Mode 24VDC-1A

This efficiency cost effective power supply is ideal for use in Fire, Access control and general security applications.

Featuring a regulated 27.6 Vdc output supplying continuous full rated current to load plus additional current for charging twox12V standby batteries.

The highly efficient switch mode design ensures low operating costs, generates less heat and with a small physical size increases the room available for additional PCBs or cables. The modular construction simplifies maintenance.



Details

- Fault and mains present indicators
- Battery disconnect to prevent deep discharge
- Tamper switch
- Fault outputs
- Mains and dc fuse
- Powder coated steel housing

PM861

Power Supply Switch Mode 24VDC-1A

Technical specifications

Electrical

Mains input	230 VAC 50 Hz \pm 10%
-------------	----------------------------

Output

Power output voltage	27.6 VDC
Output ripple	100 mV pk-pk max.
Power output current mains	1 A

Battery

Max. Battery capacity	7.2 Ah (x2)
Battery charge current	0.5 A
Battery recharge time	20 hours
Battery disconnect voltage	19.6 \pm 0.2 VDC

General

Fuse(s)	230 VAC input 2 A, 12/24 V output 1 A
---------	---------------------------------------

Physical

Physical dimensions	330 x 275 x 80 mm (W x H x D)
Colour	White
Form factor	Steel cabinet

Environmental

Operating temperature	-10 to +40°C
Relative humidity	95 %

Standards & Regulation

Compliance	CE, REACH, RoHS 2, WEEE
------------	-------------------------

Load output

0.5 A

Output ripple

Max. 100 mVrms

Open collector output

Open circuit on
fault or mains fail

Housing (steel) powder coated

1.2 mm

