

Maximum Performance

- Communicates at a distance of up to 2,000 m from the hub
- Indicates armed/disarmed states and low battery charge using a built-in LED
- Generates an audible warning if *delay* when entering/leaving mode is activated
- Indicates with sound and light when system's status changes if beep when arming/disarming mode is activated
- Features an external connector for powering a LED
- Operates up to 5 years on the pre-installed batteries

Effortless Operation

- · Adjustable sound level and alarm duration
- Two-way communication with the hub for testing and configuring

HomeSiren

Wireless indoor siren

Wireless indoor siren generates up to 105 dB at a distance of 1 m to deter burglars and attract the attention of neighbors in case of unauthorized trespassing. An inbuilt LED light and beeps indicate the system status. Moreover, the siren can power an external LED installed at the front door to warn that the property is armed.

Simple Installation



Use the QR code to connect the device to the hub



Use the SmartBracket to mount the device without disassembling it



Open the app to test connection quality and configure device settings

Bulletproof Protection



Tampering alarm



Data encryption



Device forgery prevention

Tech Specs

- · Color: white/black
- Installation: indoors
- Radio communication range: up to 2,000 m
- · Compatibility: all hubs & ReX
- Adjustable sound volume level:
 81–105 dB at a distance of 1 m
- · Adjustable alarm duration: 3-180 s
- · Temperature sensor: available
- Battery: 2x CR123A, pre-installed
- · Battery life: up to 5 years
- · Protection class of body: IP50
- Operating temperature range: from -10°C to +40°C
- Permissible humidity: up to 75%
- Dimensions: 150×103×14 mm
- Weight: 197 g