



# RF-7120-07-1

## 2-way wireless indoor siren LoNa

---

This 2-way wireless indoor siren, using the latest LoNa technology, completes your ZeroWire wireless intrusion system.

This siren can be installed easily thanks to its wireless communication, power and learn-mode technology.

It also provides the required safety and security compliant with the EN50131 regulations.

The siren is delivered with a standard 9V lithium battery & 4xAA alkaline batteries.



### Details

---

- Using LoNa technology
- Easy learn-in procedure: LED confirmation of sent and received messages
- Pry-off and opening tamper protection
- Complies with EN50131 - approvals pending
- Full wireless solution: Communication and power
- 3 years battery lifetime (based on usage)

# RF-7120-07-1

## 2-way wireless indoor siren LoNa

### Technical specifications

---

#### General

Accessory group	Siren
Type	Outdoor siren
Sounder output (dB @ distance)	101 dB at 1 m (typical)

---

#### Physical

Physical dimensions	155 x 114 x 44 mm
---------------------	-------------------

---

#### Audio frequency

	2.5 - 3 kHz
--	-------------

---

#### Battery type

	4x 1.6V AA Alkaline + 1x 9V Alkaline
--	--------------------------------------

---

#### Battery lifetime

	3 years
--	---------

---

#### Operating frequency

	433 MHz
--	---------

---

#### Compatible with

	Interlogix LoNa transceiver (i.e: ZeroWire)
--	---

---

#### Wireless

Max output power	25mW
------------------	------

---

#### Open-air range

	400m
--	------

---



As a company of innovation, Carrier Fire & Security reserves the right to change product specifications without notice. For the latest product specifications, visit [firesecurityproducts.com](http://firesecurityproducts.com) online or contact your sales representative.

Last updated on 2 September 2022 - 11:08