



# RF-7220-07-1

## 2-way wireless outdoor siren LoNa

---

This 2-way wireless outdoor siren, using the latest LoNa technology, completes your ZeroWire or Xgen wireless intrusion system. This siren installs easily because of its wireless communication, power and learn-mode technology. It also provides the required safety and security compliant with the EN50131-regulations. The custom lithium battery pack (BS7201-N) typically delivers a 3-year lifetime (based on usage).



### Details

---

- Using LoNa technology
- Easy learn-in procedure: LED confirmation of sent and received messages
- Pry-off and opening tamper protection
- Complies with EN50131
- Full wireless solution: communication and power
- 3 years of battery life (based on usage)

# RF-7220-07-1

## 2-way wireless outdoor siren LoNa

### Technical specifications

---

#### General

Accessory group	Siren
Type	Outdoor siren
Sounder output (dB @ distance)	116 dB at 1 m (typical)

---

#### Flash specifications

Light output	100,000 peak lumens
Flash frequency	60/minute

---

#### Physical

Physical dimensions	300 x 210 x 87 mm
Material	Polycarbonate

---

#### Beacon:

Spike suppression network	standard fitted
---------------------------	-----------------

---

#### Battery lifetime

	3 years
--	---------

---

#### Operating frequency

	433 MHz
--	---------

---

#### Compatible with

	Interlogix LoNa transceivers (e.g: ZeroWire)
--	--

---

#### Wireless

Max output power	25mW
------------------	------

---

#### Open-air range

	400m
--	------

---



As a company of innovation, Carrier Fire & Security reserves the right to change product specifications without notice. For the latest product specifications, visit [firesecurityproducts.com](http://firesecurityproducts.com) online or contact your sales representative.

Last updated on 2 September 2022 - 11:08